

AeGIS 7000 Series

MULTI-TENANT DEDICATED PHONE LINE SYSTEM

- PROGRAMMABLE HANDS FREE SYSTEM
- PROGRAMMABLE 4-DIGIT ACCESS CODES
- CELLULAR PHONE COMPATIBLE
- POSTAL LOCK READY
- SINGLE LINE BACKLIT ELECTRONIC DIRECTORY LCD
- BUILT-IN NIGHT LIGHTS
- SINGLE RELAY
- BRUSH STAINLESS STEEL FACE-PLATE
- INDOOR OR OUTDOOR



SPECIFICATIONS

POWER INPUT: 12VAC/40VA (supplied) or 12VDC/40VA (output reading must be 13.5 - 14.5 VDC).
CURRENT CONSUMPTION: 500mA idle, 700mA operating.
EMERGENCY BATTERY: Built-in charging circuit for 12VDC/4Ahr rechargeable battery (battery is not supplied).
OPERATING ENVIRONMENT: 32°F to 140°F. Humidity 0%-95% non-condensing. **Heater is required if the temperature is below 32°F.**
MEMORY: EEPROM (non-volatile).

MOUNTING: Surface and full-flush.
DIMENSIONS:
Surface 10-13/16" (H) x 8-5/8" (W) x 3-3/4" (D).
Full-flush 10-13/16" (H) x 8-3/8" (W) x 2-7/16" (D)
MOUNTING RING FULL-FLUSH (FFM7 is included):
Inside 11-1/8" (H) x 8-11/16" (W) x 2-5/8" (D)
Outside 14-5/16" (H) x 12-1/8" (W)
Warranty: Two Years (24 months)

ORDER PART NUMBER

SURFACE MOUNT BRUSHED STAINLESS STEEL
7150 150 tenants and 150 access codes
7250 250 tenants and 250 access codes

FULL-FLUSH MOUNT BRUSHED STAINLESS STEEL
7150FF 150 tenants and 150 access codes
7250FF 250 tenants and 250 access codes
Mounting Ring (FFM7) is included.

ACCESSORIES

[Radio Receiver and Transmitter](#)
ARFR Radio Frequency Receiver
ARFT Radio Frequency Transmitter
ARFHT Radio Frequency Handheld Transmitter.
[Pedestal Mounting Post, Adapter Plate and Mounting Ring](#)
UPM1S Standard Single Arm Pedestal Mounting Post
UPM1L Large Single Arm Pedestal Mounting Post
UPM2 Double Vertical Arm Pedestal Mounting Post
UPM5 Double Horizontal Arm Pedestal Mounting Post
UPMDB64 Single Arm Direct Buriel Pedestal Mounting Post
UAP78 Adapter Plate for mounting the AeGIS 7000 Series
[Video Package](#)
AVP7C AeGIS Color Video Package.

[Miscellaneous Accessories](#)
FFM7 Full-flush mounting ring, included with full-flush system.
ASP1 AC and Telephone Surge Protector.
AHP5 Heater Pad with Thermostat.
ABAT1 12VDC 4.5 Ahr backup battery.
ARIGB7 Rough-in box.
ADIR Paper Directory

Specifications and Warranty subject to change without prior notice

PACH & COMPANY
www.pach-co.com

941 Calle Negocio
San Clemente, CA 92673

Phone: 888-678-7224
Fax: 949-498-6879